

POWER-SUPPLY (SWITCH-MODE) - MX6000D-150KG

Category: Microwave generators



BILDERGALERIE



ADDITIONAL INFORMATION

| | |
|--|--|
| Typ | Power-Supply |
| Frequency [MHz] | 2450 |
| Output Power CW [W] | 6000 |
| Line connection | 3~ (L1 / L2 / L3 / PE) |
| Control circuit connection [V] | |
| Line Voltage [V] | 208 |
| Mains voltage control circuit [V] | |
| Line Frequency [Hz] | 50 / 60 |
| Cooling | Air / Water, Air / Water |
| Pulse output power max [W] | 6000 |
| Front-Panel (HMI) | Operating Unit with Main Switch, Operating Unit with Main Switch |
| Interface | front display |
| Interface 2 | Can-Bus |
| Interface 3 | A/D |
| Interface 4 | RS-232 |
| Interface 5 | - |
| Width [mm (inch)] | 484 (19,06) |
| Height [mm (inch)] | 128 (5,04) |
| Depth [mm (inch)] | 607 (23,90) |
| Protection Class | IP20 |
| Isolator | No |
| Related Magnetron Head | MH6000S-250BF, MH6000S-251BF |
| Power-Supply | Switch-Mode |